

USB変換基板間ピンアサイン一覧表

USB245		USB245R		USB2232		USB232R		USB232		USB232P		USB234X	
1.	D0	D0		1.	ADBUS0(D0)	BDBUS0(TXD)	1.	TXD	TXD	1.	CTS#	GND	
2.	D1	D1		2.	ADBUS1(D1)	BDBUS1(RXD)	2.	RXD	RXD	2.	DCD#	TXD	
3.	D2	D2		3.	ADBUS2(D2)	BDBUS2(RTS#)	3.	RTS#	RTS#	3.	DSR#	RXD	
4.	D3	D3		4.	ADBUS3(D3)	BDBUS3(CTS#)	4.	CTS#	CTS#	4.	RI#	RTS#	
5.	D4	D4		5.	ADBUS4(D4)	BDBUS4(DTR#)	5.	DTR#	DTR#	5.	RXD	CTS#	
6.	D5	D5		6.	ADBUS5(D5)	BDBUS5(DSR#)	6.	DSR#	DSR#	6.	RTS#	VCCIO	
7.	D6	D6		7.	ADBUS6(D6)	BDBUS6(DCD#)	7.	DCD#	DCD#	7.	DTR#		(6P*1列)
8.	D7	D7		8.	ADBUS7(D7)	BDBUS7(RI#)	8.	RI#	RI#	8.	TXD		
9.	WR	RXF#		9.	ACBUS0(RXF#)	BCBUS0(TXDEN)	9.	CBUS0(TXLED#)	PWREN#	9.	VCCIO		
10.	RD#	TXE#		10.	ACBUS1(TXE#)	BCBUS1(SLEEP#)	10.	CBUS1(RXLED#)	TXDEN	10.	GND		
11.	TXE#	RD#		11.	ACBUS2(RD#)	BCBUS2(RXLED#)	11.	CBUS2(TXDEN)	PWRCTRL	11.			
12.	RXF#	WR		12.	ACBUS3(WR)	BCBUS3(TXLED#)	12.	CBUS3(PWREN#)	TXLED#	12.			
13.	PWREN#	PWREN#		13.	PWREN#	PWREN#	13.	CBUS4(SLEEP#)	SLEEP#	13.			
14.	SI/WU	OSCI		14.	SI/WUA	SI/WUB	14.	OSCI	RXLED#	14.			
15.	+3.3V	+3.3V		15.	+3.3V	+3.3V	15.	+3.3V	+3.3V	15.			
16.	RESET#	RESET#		16.	RESET#	RESET#	16.	RESET#	RESET#	16.			
17.	VCCIO	VCCIO		17.	VCCIOA	VCCIOB	17.	VCCIO	VCCIO	17.			
18.	VCC+5V	VCC+5V		18.	VCC+5V	VCC+5V	18.	VCC+5V	VCC+5V	18.			
19.	GND	GND		19.	GND	GND	19.	GND	GND	19.			
20.	GND	GND		20.	GND	GND	20.	GND	GND	20.			

ツール工房(有)